



Construction of two New Second Order Rotatable Designs Using Trigonometric Functions

Nyakundi Omwando Cornelious^{a*} and Japheth Maisiba Ogega^a

^a Department of Mathematics and Physical Sciences, Maasai Mara University, Narok, Kenya.

Authors' contributions

This work was carried out in collaboration between both authors. Both authors read and approved the final manuscript.

Article Information

DOI: <https://doi.org/10.9734/ajpas/2024/v26i6623>

Open Peer Review History:

This journal follows the Advanced Open Peer Review policy. Identity of the Reviewers, Editor(s) and additional Reviewers, peer review comments, different versions of the manuscript, comments of the editors, etc are available here: <https://www.sdiarticle5.com/review-history/117877>

Original Research Article

Received: 21/03/2024

Accepted: 25/05/2024

Published: 03/06/2024

Abstract

In this study, two new second order rotatable designs of thirty-five and forty-five points are constructed respectively using transformations of some trigonometric functions. The designs are rotatable since they satisfy both the outlined moment conditions and the non-singularity conditions. Second-order rotatable designs are useful for optimizing these processes in chemical industries, agriculture and engineering by systematically varying the factors of interest and studying their combined effects on the response variables. This helps in identifying the optimal settings for maximum or minimum responses.

Keywords: Second order; rotatable designs; response surface.

*Corresponding author: Email: nyakundicornelious@yahoo.com;

1 Introduction

In any experimental work, it is important to choose the best design in a class of existing designs. The choice is solely dependent of the interest of the experimenter and the adequacy of an experimental design that can be determined from the information matrix, Box [1]. The technique of fitting a response surface is one widely used to aid in the statistical analysis of experimental work in which the yield of a product depends in some unknown fashion on one or more controllable variables, Bose and Draper [2]. Before the details of such an analysis can be carried out, experiments must be performed at predetermined levels of controllable factors, i.e. an experimental design must be performed prior to experimentation. Box and Hunter [3] suggested designs of a certain type which they called rotatable as being suitable for such experimentation. They developed second order rotatable designs through geometrical configurations. Box and Wilson [4] pointed out that the technique of fitting a response surface is one widely used to aid in the statistical analysis of experimental work in which the response of the product depends in some unknown fashion, on one or more controllable variables. Mutiso [5] constructed specific optimal second order rotatable designs in three, four and five dimensions. Koske *et al.* [6,7,8] constructed optimal second order rotatable designs and gave practical hypothetical examples. Cornelious [9,10,11,12] constructed optimal sequential third order rotatable designs in three four and five dimensions, and a second order rotatable design of 33, 39 and 42 points respectively in three dimensions giving practical hypothetical examples. The current study gives new 35- points, and 45-Points second order rotatable designs in three dimensions constructed using transformations of Trigonometric functions [13,14].

2 Methods

2.1 Moment conditions for second order rotatability

Suppose a second order response surface is to be fitted, then the following model is ideal;

$$y_u = \beta_0 + \sum_{i=1}^N \beta_i x_{iu} + \sum_{i=1}^N \beta_{ii} x_{iu}^2 + \sum_{i,j=1}^N \beta_{ij} x_{iu} x_{ju} + e_u \quad (1)$$

Where x_i denotes the level of the i^{th} factor ($i=1,2,3\dots k$) in the u^{th} run, ($u=1,2,3\dots, N$) of the experiment and e_u is the un correlated random error with mean zero and variance σ^2 .

According to Box and Hunter [3], A second order response surface is achieved if the design points satisfy the following moment conditions.

- i. $\sum_{u=1}^N x_{iu}^2 = N\lambda_2$ (2)
- ii. $\sum_{u=1}^N x_{iu}^4 = 3N\lambda_4$ (3)
- iii. $\sum_{u=1}^N x_{iu}^2 x_{ju}^2 = N\lambda_4$ for ($i \neq j = 1, 2, \dots, k$) and $3, \lambda_2, \lambda_4$, are constants.
- iv. $\sum_{u=1}^N x_{iu}^4 - 3 \sum_{u=1}^N x_{iu}^2 x_{ju}^2 = 0$ (4)
- v. All the other odd order moments are zero.

If all the above conditions are satisfied, then the set of points is said to form a rotatable arrangement.

2.2 Non-singularity conditions for second order rotatability

For the second order rotatable design to exist, the following non-singularity conditions must also be satisfied.

$$\frac{\lambda_4}{\lambda_2^2} > \frac{k}{k+2} \quad (5)$$

Where k is the number of factors which in this case will be 3, and, λ_2 , and λ_4 are obtained from the moment conditions given in (1), (2) and (3).

2.3 3s- Points

Trigonometric functions were first introduced by Bose and Draper [7] in the construction of second order rotatable designs. They introduced transformations of the form,

$$T_1 = \begin{bmatrix} \cos \alpha, -\sin \alpha, 0 \\ \sin \alpha, \cos \alpha, 0 \\ 0 & 0 & -1 \end{bmatrix} \tag{6}$$

And

$$T_2 = \begin{bmatrix} \cos \frac{\alpha}{2}, \sin \frac{\alpha}{2}, 0 \\ \sin \frac{\alpha}{2}, \cos \frac{\alpha}{2}, 0 \\ 0 & 0 & -1 \end{bmatrix} \tag{7}$$

Where $\alpha = \frac{2\pi}{s}$

These transformations are applied in the current study to construct second order rotatable designs. The transformations given in (6) and (7) are applied to the point sets of the form $G(r, 0, b)$, i.e., points on the plane $y = 0$, and to all other points obtained from repeated applications of T_1 and T_2 .

The permutation group (I, W, W^2) generated by,

$$W = \begin{bmatrix} 0 & 1 & 0 \\ 0 & 0 & 1 \\ 1 & 0 & 0 \end{bmatrix}, \tag{8}$$

shall also be applied to $G(r, o, b)$ to give $T_z(r,o,b)$, $T_x(b,r,o)$ and $T_y(o,b,r)$.

Consider a set $T(r, 0, b)$. Assuming $b = 0$, then $T(r, 0, b)$ becomes $T(r, 0, 0)$. Applying (6) and (8) respectively on $T(r,0,0)$ gives the following set of coordinates,

$$(r \cos t\alpha, r \sin t\alpha, 0), (r \sin t\alpha, 0, r \cos t\alpha), (0, r \cos t\alpha, r \sin t\alpha) \tag{12}$$

Where; $t = 0, 1, 2, \dots (s-1)$ and $s \geq 5$.

The sums and products of the set up to power four for the co-ordinates listed in (12) are given by;

$$\sum_{u=1}^N x_{iu}^2 = sr^2, \sum_{u=1}^N x_{iu}^4 = \frac{3}{4}sr^4, \sum_{u=1}^N x_{iu}^2 x_{ju}^2 = \frac{1}{8}sr^4, \tag{13}$$

The excess function for $T(r, o, o)$ is given by;

$$\sum_{u=1}^N x_{iu}^4 - 3\sum_{u=1}^N x_{iu}^2 x_{ju}^2 = \frac{3}{8}sr^4 \tag{14}$$

2.4 Eight point set

Similarly, the co-ordinates for the eight points set denoted $G(a, a, a)$ are as listed below,

$$\begin{aligned} &G(a, a, a), G(-a, a, a), G(a, -a, a), G(a, a, -a) \\ &G(-a, -a, a), G(-a, a, -a), G(a, -a, -a), G(-a, -a, -a) \end{aligned} \tag{15}$$

The sums and products up to power four for $G(a, a, a)$ is given by,

$$\begin{aligned} \sum_{u=1}^N x_{iu}^2 &= 8a^2 \\ \sum_{u=1}^N x_{iu}^4 &= 8a^4 \\ \sum_{u=1}^N x_{iu}^2 x_{ju}^2 &= 8a^4 \end{aligned} \tag{16}$$

The excess for the above set of points is given by

$$\sum_{u=1}^N x_{iu}^4 - 3\sum_{u=1}^N x_{iu}^2 x_{ju}^2 = -16a^4 \tag{17}$$

2.5 The twelve point set

Consequently, the co-ordinates for the twelve-point set denoted by G (p, p, o) are listed as given below.

$$\begin{aligned} &G (p, p, 0), G (-p, p, 0), G (p, -p, 0), G (-p, -p, 0) \\ &G (0, p, p), G (0, -p, p), G (0, p, -p), G (0, -p, -p) \\ &G (p, 0, p), G (-p, 0, p), G (p, 0, -p), G (-p, 0, -p) \end{aligned} \tag{18}$$

The sums and products up to the power four for G (p, p, o), are given by,

$$\sum_{u=1}^N x_{iu}^2 = 8p^2, \sum_{u=1}^N x_{iu}^4 = 8p^4, \sum_{u=1}^N x_{iu}^2 x_{ju}^2 = 4p^4 \tag{19}$$

The excess for the above set of points is given by

$$\sum_{u=1}^N x_{iu}^4 - 3\sum_{u=1}^N x_{iu}^2 x_{ju}^2 = -4p^4 \tag{20}$$

2.6 The twenty-four point set

Finally, the co-ordinates for the twenty-four points set denoted by G (p, q, o) are listed as given below.

$$\begin{aligned} &G (q, p, 0), G (-q, p, 0), G (q, -p, 0), G (-q, -p, 0) \\ &G (p, q, 0), G (-p, q, 0), G (p, -q, 0), G (-p, -q, 0) \\ &G (0, p, q), G (0, -p, q), G (0, p, -q), G (0, -p, -q) \\ &G (0, q, p), G (0, -q, p), G (0, q, -p), G (0, -q, -p) \\ &G (p, 0, q), G (-p, 0, q), G (p, 0, -q), G (-p, 0, -q) \\ &G (q, 0, p), G (-q, 0, p), G (q, 0, -p), G (-q, 0, -p) \end{aligned} \tag{21}$$

The sums and products up to the power four for G (p, q, 0), are given by,

$$\sum_{u=1}^N x_{iu}^2 = 8p^2 + 8q^2, \sum_{u=1}^N x_{iu}^4 = 8p^4 + 8q^4, \sum_{u=1}^N x_{iu}^2 x_{ju}^2 = 8p^2 q^2 \tag{22}$$

The excess for the above set of points is given by

$$\sum_{u=1}^N x_{iu}^4 - 3\sum_{u=1}^N x_{iu}^2 x_{ju}^2 = 8p^4 + 8q^4 - 24 p^2 q^2 \tag{23}$$

3 Results and Discussion

3.1 Construction of thirty-five points second order rotatable design in three dimensions

The thirty-five points is obtained by combining three sets i.e. the set denoted by s_1, s_2, s_3 .

Where;

$$s_1 = 3s \text{ for } s=5 \text{ given in (12), } s_2 = 2 G (p, p, 0) \text{ given in (18), and } s_3 = s (a, a, a) \text{ given in (15).}$$

The sums of squares for the combined sets (12) and (15) and (18) up to the power of four gives

$$\begin{aligned} \sum_{u=1}^{35} x_{iu}^2 &= Sr^2 + 8p^2 + 8 a^2 \\ \sum_{u=1}^{35} x_{iu}^4 &= \frac{3}{4}Sr^4 + 8p^4 + 8 a^4 \\ \sum_{u=1}^{35} x_{iu}^2 x_{ju}^2 &= \frac{1}{8}Sr^4 + 4p^4 + 8 a^4 \end{aligned} \tag{24}$$

And all other odd odder powers are zero

The set of thirty-five points denoted by R_3 is given by;

$$R_3 = s(p, p, 0) + s(a, a,) + 3s \tag{25}$$

Substituting (24) to the moment conditions given in (2),(3),(4) gives;

$$\begin{aligned} Sr^2 + 8p^2 + 8a^2 &= N\lambda_2, \frac{3}{4}Sr^4 + 8p^4 + 8a^4 = 3N\lambda_4, \\ \frac{1}{8}Sr^4 + 4p^4 + 8a^4 &= N\lambda_4. \end{aligned} \tag{26}$$

The excess function for s_1 given in (14) is added to the excess function for s_2 and s_3 given in (17) and (20) respectively assuming the value of S to be 5 to give;

$$\sum_{u=1}^{35} x_{iu}^4 = 3\sum_{u=1}^{35} x_{iu}^2 x_{ju}^2 = \frac{15}{8}sr^4 - 4p^4 - 16a^4 = 0 \tag{27}$$

Equation (27) is solved to obtain the values of p and a in terms of r as follows;

$$\text{Let } p^2 = xr^2 \text{ and } a^2 = yr^2 \tag{28}$$

Substituting (28) to (27) gives

$$1.875r^4 - 4x^2r^4 - 16y^2r^4 = 0 \tag{29}$$

Making x the subject of the formula in (29) results to;

$$x = \sqrt{0.1171875 - 0.25y^2} \tag{30}$$

The values of y which together with the corresponding values of x makes real and positive values are;

$$0 \leq y \leq 0.632455532, \tag{31}$$

Taking an arbitrary value of x to be 0.05, the corresponding value of y is 0.341412507,

Substituting the values of x and y to (28) gives

$$p^2 = 0.05r^2, a^2 = 0.341412507r^2 \tag{32}$$

Substituting (32) to (26) for the value of $s = 5$ gives,

$$\lambda_2 = 0.232322858p^2, \lambda_4 = 0.044785714p^4 \tag{33}$$

Substituting (33) to the non-singularity conditions given in (2), (3) and (4) for $k=3$ factors proves that the condition in (5) is satisfied thus the 35 points forms a second order rotatable design in three dimensions [15].

3.2 Construction of forty-five points second order rotatable design in three dimensions

The forty-five points is obtained by combining two sets i.e. the set denoted by s_1 and s_5 ,

Where;

$$\begin{aligned} s_1 &= 3s \text{ for } s=5 \text{ given in (12)} \\ s_4 &= s(p, q, 0) \text{ given in (21)} \end{aligned}$$

The sums of squares for the combined sets (12) and (21) up to the power of four gives

$$\begin{aligned} \sum_{u=1}^{45} x_{iu}^2 &= Sr^2 + 8p^2 + 8q^2 \\ \sum_{u=1}^{45} x_{iu}^4 &= \frac{3}{4}Sr^4 + 8p^4 + 8q^4 \\ \sum_{u=1}^{45} x_{iu}^2 x_{ju}^2 &= \frac{1}{8}Sr^4 + 8p^2q^2 \end{aligned} \tag{34}$$

And all other odd powers are zero

The set of forty-five points denoted by R_6 is given by;

$$R_6 = 3s + s(p, q, 0) \tag{35}$$

Subjecting (34) to the moment conditions given in (2),(3), and (4) results to,

$$Sr^2 + 8p^2 + 8q^2 = N\lambda_2, \frac{3}{4}Sr^4 + 8p^4 + 8q^4 = 3N\lambda_4, \frac{1}{8}Sr^4 + 8p^2q^2 = N\lambda_4 \tag{36}$$

The excess function for s_1 given in (14) is added to the excess function for s_5 given in (23) assuming the value of $S=7$ to give;

$$\sum_{u=1}^{45} x_{iu}^4 = 3\sum_{u=1}^{45} x_{iu}^2 x_{ju}^2 = \frac{21}{8}r^4 + 8p^4 + 8q^4 - 24p^2q^2 = 0 \tag{37}$$

Equation (37) is solved to obtain the values of p and q in terms of r as follows;

$$\text{Let } p^2 = xr^2 \text{ and } q = yr^2 \tag{38}$$

Substituting (38) to (37) gives;

$$2.625r^4 + 8x^2r^4 + 8y^2r^4 - 24x^2y^2r^4 = 0 \tag{39}$$

Making x the subject of the formula in (39) results to;

$$x = \frac{24y \pm \sqrt{320y^2 - 84}}{16} \tag{40}$$

The values of y which together with the corresponding values of x makes real and positive values are;

$$y \geq 0.05124, \tag{41}$$

Taking an arbitrary value of x to be 0.54, the corresponding value of y is 0.6192776888. Substituting the values of x and y to (38) gives

$$p^2 = 0.54r^2, q^2 = 0.6192776888r^2 \tag{42}$$

Substituting (42) to (36) for the value of $s = 7$ gives,

$$\lambda_2 = 0.3616493667r^2, \lambda_4 = 0.07889510257r^4 \tag{43}$$

Substituting (43) to the non-singularity conditions given in (2),(3),and (4) for $k=3$ factors proves that the condition in (5) is satisfied thus the 45 points forms a second order rotatable design in three dimensions.

4 Conclusions and Recommendations

The response surface methodology in this case is used to approximate the functional relationship between the performance characteristics and the design variables. After experimentation, the resulting response is used to construct response surface approximation model using least squares regression analysis. This study recommends the extension of this class of designs to more than three factors to cater for experiments where more than three factors are required.

Competing Interests

Authors have declared that no competing interests exist.

References

- [1] Box GE. multifactor designs of first order, *journal of Biometrika*. 1952;39:49-57.
- [2] Bose RC. Draper, second order rotatable designs in three dimensions, *Annals of mathematical statistics*. 1959;30:1097-1112.
- [3] Box GEP, Hunter JS. Multifactor experimental designs for exploring response surfaces. *Annals of mathematical statistics*. 1957;28:195-241.
- [4] Box GEP, Wilson KB. On experimental attainment of optimum conditions, *journal of Royal statistical society.Ser*. 1951;13:49-57.
- [5] Mutiso JM. Second and third order specific and sequential rotatable designs in K dimensions, D.Phil. Thesis, Moi University, Eldoret, Kenya; 1998.
- [6] Koske JK, Mutiso JM, Kosgei MK. A specific optimum second order rotatable design of 24 points with a practical example, Moi University, Eldoret, Kenya; 2008.
- [7] Koske JK, Mutiso JM, Kosgei MK. A specific optimum second order rotatable design in three dimensions, *Advances and Applications in Statistics*. 2012;30:31-43.
- [8] Koske JK, Mutiso JM, Tum IK. Construction of practical optimum second order rotatable design in three dimensions, *Advances and Applications in Statistics*. 2012;30:31-43.
- [9] Cornelious NO. optimal sequential third order rotatable designs in three, four and five dimensions, M.Phil. Thesis, Moi University, Eldoret, Kenya; 2016.
- [10] Cornelious NO. construction of thirty-nine points second order rotatable design in three dimensions with a hypothetical example. *European International Journal of science and technology*. 2019;8:51-57.
- [11] Cornelious NO, construction of thirty-six points second order rotatable design in three dimensions with a practical hypothetical case study. *International journal of advances in scientific research and Engineering*. 2019;6:111-118.
- [12] Nyakundi Omwando Cornelious. A Forty-Two Points Second Order Rotatable Design in Three Dimensions Constructed using Trigonometric Functions Transformations. *International Journal of Advances in Scientific Research and Engineering (IJASRE)*; 2024. ISSN:2454-8006, DOI: 10.31695/IJASRE, 10(5), 10–14. Available:<https://doi.org/10.31695/IJASRE.2024.5.2>
- [13] Mwan DM, Kosgei MK, Rambaei SK. DT- optimality Criteria for Second Order Rotatable Designs Constructed Using Balanced Incomplete Block Design. *J. Adv. Math. Com. Sci.* [Internet]. 2017 Jul. 17 [cited 2024 May 21];22(6):1-7. Available:<https://journaljamcs.com/index.php/JAMCS/article/view/200>
- [14] Chiranjeevi P, Victorbabu BR. Second Order Rotatable Designs of Second Type Using Pairwise Balanced Designs. *Asian Res. J. Math.* [Internet]. 2021 Mar. 25 [cited 2024 May 21];17(2):20-33. Available:<https://journalarjom.com/index.php/ARJOM/article/view/448>

- [15] Kim J, Bhattacharyya G, Mukherjee S, Das RN. Robust second-order rotatable invariably designs for some lifetime distributions. *Communications in Statistics-Theory and Methods*. 2023;52(9):2819-35.

© Copyright (2024): Author(s). The licensee is the journal publisher. This is an Open Access article distributed under the terms of the Creative Commons Attribution License (<http://creativecommons.org/licenses/by/4.0>), which permits unrestricted use, distribution, and reproduction in any medium, provided the original work is properly cited.

Peer-review history:

The peer review history for this paper can be accessed here:

<https://www.sdiarticle5.com/review-history/117877>